

How do I change Time-Date on 'phone system' ?

" COMDIAL" IMPACT - DIGITECH (DSU/DSU II)

2.8 Setting The System Clock

You can program the system clock to maintain current date and time information. The time and date appear on the LCD speakerphone for display.

- To set the system clock from the 'Attendant Station' (Ext.10, Ext.12)
 1. Press INTERCOM
 2. Dial * # 0 1
 3. Dial two digits (00-99) for year.
 4. Dial two digits (01-12) for month.
 5. Dial two digits (01-31) for day.
 6. Dial two digits (00-23) for hour.
 7. Dial two digits (00-59) for minutes.
 8. Press SPEAKER to end.

From page 2-14 of the LCD Speakerphone Reference Manual.

"COMDIAL" CONVERSip EP100 - IMPACT (DXP, FXII , MP5000)

System Clock

The system clock provides a date and time for display at LCD speakerphones connected to the system.

- To set the system clock from the 'Attendant Station' / 'Receptionist Phone'
 1. Press INTERCOM
 2. Dial * # 0 * 0 1
 3. Dial two digits (01-12) for month.
 4. Dial two digits (01-31) for day.
 5. Dial two digits (00-99) for year.
 6. Dial two digits (00-23) for hour.
 7. Dial two digits (00-59) for minute.
 8. Dial # to save.
 9. Press SPEAKER to end.

From page 114 of the Attendant Manual - Impact 224/560/FX Systems.

"COMDIAL" DX-80 / DX-120

Setting the System Clock (From any telephone extension)

Perform these steps with your Handset "On-Hook" (Hung Up)

1. Enter Database....FEATURE # * ##### (8 #'s)
2. Press [show]
3. Input 08-03, then press [save]. This advances to Hour Mode programming screen
4. Press [chg] to change to select 12/24 Hour Mode
5. Input 08-14, then press [save]. This advances to the System Time programming

screen

6. Press [show], the Year database item displays
7. Press [chg] to change the year for the system clock.
or...
Press [next] to advance to the next system clock item that requires changes
8. Press [chg] and input data as required
9. Follow this convention for each of the database items for the system clock.
10. Press HOLD to exit System Time programming and return to the previous menu

level.

11. Exit the programming mode

" SAMSUNG "

MMC:505 Assign Date and Time (From any telephone extension)

- 1.) Press " Transfer " button (TRSF), dial 200
- 2.) PASSCODE: 1234
- 3.) Dial 1 to ENABLE programming
- 4.) Press " Transfer " button to store, and return to idle condition

Next... (within 60 second window)

- 5.) Press " Transfer " button (TRSF)
- 6.) ENTER PROGRAM ID: 505
- 7.) Select New Time (see table below)
- 8.) Press " Transfer" to save and exit

<u>MMC: 505 Table</u>	W	Day	0 - 6 (Sunday - Saturday)
	MM	Month	01-12
	DD	Date	01-31
	YY	Year	00-99 (1990 - 2089)
	HH	Hour	00-23 (24 hour clock time)
	MM	Minute	00-59

Change Time/Date on COMPUTERS FOR " DOS - VOICE MAIL SYSTEMS "

1. Go to a DOS prompt
2. Type time
3. Enter the new time in the format shown.
4. Press ENTER to save.
5. Power VMail Computer OFF, leave for 1 minute, power ON (Re-Boot)
6. Allow 2-3 minutes for system to re-boot; it will do this on its own